MeasuringPAD

SPECIFICATIONS

Scanning, Monitoring, and Recording

Scan Rate: 10 kHz per analog input; 10 kHz per digital input 16-bit A/D conversion

Overall Accuracy (All Measurements): ±0.1% of full scale or better Overrange (All Measurements): 10% of full scale

Logging Modes:

 Manual: A single "snapshot" record taken via touchscreen button

 Timed: Records taken automatically between specified start and stop times; user-specified rate from one second to 24 hours

 Event-Triggered: Records taken while any triggering limit violation or digital input occurs; user-specified rate from one millisecond to 24 hours, or "burst" speed (as fast as possible); overrides timed logging, and may include "pretrigger" data, if desired

 User-enabled beeper for setpoint violation alert

Test/Process Interface

Up to four external sensor interface pods per MeasuringPAD unit (ordered separately)

Four DC-coupled differential analog inputs of the same type per pod (see below)

Two digital inputs per pod (see below)

EEPROM per pod, for ID and storage of calibration values

Analog Inputs

Low Voltage Pod

Operating Range (Differential and Common-Mode): ±0 to 30 VDC or 0 to 24 VAC RMS

Input Impedance: 4 M Ω (differential); 1 M Ω (common-mode) Accuracy: ±0.1% of full scale up to 400 Hz; ±1.0% of full scale up to 5 kHz

Connection: Five-way binding posts

High Voltage Pod

Operating Range (Differential and Common-Mode): ±0 to 600 VDC or 0 to 480 VAC RMS

Input Impedance: 40 M Ω (differential); 10 M Ω (common-mode) Accuracy: ±0.1% of full scale up to 400 Hz; ±1.0% of full scale up to 5 kHz

Connection: Safety banana jacks

Low Current

Operating Range (Differential): ± 0 to 20 mADC or 0 to 20 mAAC RMS

Input Impedance: 250 Ω (differential); 1 M Ω (common-mode) Accuracy: ±0.1% of full scale up to 400 Hz; ±1.0% of full

scale up to 5 kHz

Connection: Five-way binding posts

Thermocouple

Accepts Types B, E, J, K, N, R, S, and T

Test / Process Interface (continued)

Resolution: 0.1 degree Input linearization via NIST table Accuracy: ±0.1% of full scale DC ± 0.5° C cold-junction compensation Connection: Mini jacks Digital Inputs (All Pods, unless otherwise indicated)

 $\begin{array}{l} \mbox{Maximum Frequency: 20 kHz} \\ \mbox{Minimum Time Interval (for timed inputs): 1 msec} \\ \mbox{V}_{\rm H}: 4.5 to 24 VDC \\ \mbox{V}_{\rm L}: 0 to 0.6 VDC \\ \mbox{R}_{\rm H}: 6.0 k\Omega, approximate \\ \mbox{Isolation: Optically isolated to 750 VAC RMS, common-mode} \\ \mbox{Frequency and quadrature inputs configurable for limit logic} \end{array}$

Connection: Five-way binding posts

DC Strain Gauge

1, 2, 4 & 10 mV/V Accuracy: ±0.1% of full scale up to 400 Hz; ±1.0% of full scale up to 5 kHz Connection: Screw Terminals

Connection: Screw Terminais

General Specifications

Dimensions (HWD): 12" x 2.5" x 8" (30 cm x 6.4 cm x 20.3 cm) Weight: 4.2 lb. (1.9 kg)

Operating Temperature: -10° to 50° C (14° to 122° F) Storage Temperature: -40° to 85° C (-40° to 185° F)

Humidity: 95%, noncondensing

System Time Clock: Crystal-controlled; 1-second resolution

Display: Contrast-adjustable 320 x 240 LCD color touchscreen with audible feedback and programmable backlight timeout; available languages include English, French, Italian, German, Spanish

Memory Card: Compact flash 256M supplied

AC Power Adapter supplied (90-264 VAC, 47-63 Hz) Supporting easel and carry strap supplied

Optional Accessories

Low Voltage and High Voltage Cable Sets Soft-Sided Carrying Case Field-Replaceable Battery Pack External Battery Charger Weatherproof Container Reusable Shipping Container Lockable Portable Case USB Flash Card Reader Current Probes: TR25XX (1-3000A) Clamp-on RR30XX (30/300/3000A) Flexible



MEASURING

A versatile, short-term data acquisition solution for maintenance, troubleshooting and energy measurement applications



102

For temporary but critical on-site data acquisition, the portable, high-speed MeasuringPADTM offers a convenient, economical alternative to an elaborate test and measurement installation. This sturdy hand-held instrument can be used in a wide range of manufacturing, laboratory, plant operations, and quality control applications. Rapidly collecting, monitoring, and displaying multiple sensor inputs, it can be used for troubleshooting, maintenance, process tuning, fault recording, trend analysis, and much more. Configured and operated through an easy-to-use color touchscreen interface, MeasuringPAD continuously scans all active inputs, digitizing with 16-bit A/D while checking for limit-violation triggers and refreshing its memory buffer of 10 kHz per input.

Real-Time Data Monitoring

MeasuringPAD provides live readout of up to sixteen differential analog inputs and up to eight logic-level digital inputs. As numerical measurements are monitored for exact conformance to user-entered setpoints, the vivid color-coded status display

R1: Volts R1		
483.42		
A2: Volts A2	AD1:	
481.67	956.2k	
A3: Volts A3	AD2:	
480.89	OFF	
R4: Volts R4		
0.7653		

R1: TagR1	Cl: TagC1	
A2: TagAZ	C2: TagC2	L1: TagL1
A3: TagA3	C3: TagC3	L2: TagL2
A4: TagA4	C4: TagC4	
AD1: TagAD1	CD1: TagCD1	L3: TagL3
SURgeT 150A	CD2: TagCD2	L4: TagL4
Pod B	Pod D	
B1: TagB1	01: TagD1	L5: TagL5
82: Tag82	D2: TagD2	L6: TagL6
B3: TagB3	🔲 D3: TagD3	
B4: Tag84	D4: TagD4	L7: TagL7
801: Tag8D1	🔲 001: TagDD1	
802: Tag802	5002: Tag002	L8: TagL8


lets you size up your test or process at a glance. To ensure true "finished-answer" readability, analog signals are easily scalable to desired engineering units.

Convenient input "pods" allow fast and easy hookup of machine- or process-dedicated sensors - including DC/AC Low and High Voltage sources (from 100 mV to 300 V), DC/AC Low Current sources (4 to 20 mA), and most Thermocouple types. Digital inputs are standard TTL-level signals from switches, contacts, encoders, pickups, and other frequency-generating devices. They may be used to trigger the logging of data, to perform programmable counting and timing operations, and to monitor frequency and quadrature. Up to eight internal

cross-channel math calculations can also be set up to display and monitor additional process variables such as horsepower, efficiency, and corrected flow - plus signal max/min and average values.

High-Speed Data Recording

You can instruct MeasuringPAD to sample scaled measurements at a regular time interval - or, immediately on detection of any specified trigger event, to begin recording at a special rate that can be up to a microsecond-level "burst" speed. Instantly stored on a standard CF memory card in a simple and universally compatible ASCII text format, data records are both time- and trigger-stamped, and may be directly imported by all kinds of third-party programs for post-analysis and report generation, without the need for special drivers or version-dependent operating



systems. If desired, records of data values as they existed just prior to a triggering event can be included in the stored data file. The touch of a button will display a scrollable spreadsheet report of all currently logged data, including time and event indication.









Multichannel Data Display

For instant operator interpretation of measurement results, the backlit color LCD furnishes real-time display of measured and calculated values in a number of programmable formats, inc

- bargraph, for rapid visual comparison of up to sixteen active parameters
- trend, for simultaneous, independent timeplotting of up to four active parameters. Ideal for comparing energy and process/ production parameters for energy reduction studies.
- scope, for live display of up to four active waveform inputs in a conventional oscilloscope mode
- discrete Fourier transform (DFT), for harmonic analysis of a selected analog input.







Using MeasurePAD's unique touchscreen pages, setting up the

Global Setting	Calculates Configura	ation
Secting	11/12/13/14	L5 16 17 L
Input Config	Enable	L4 = 120 • RYG(C1) +
Calculates Config	Tag: Power	Legend: Watts
	Equation: y = m +	RYG(x) + b
Threshold Config	m = 120.0	x = C1 (Amps C1)
Site Name/ Memory	b = 0	
_		Prev Next Cano
Global	Threshold Configur.	
Glob al Setting		ation
	Threshold Configur.	ation
Setting	Threshold Configure Pod B/Pod B/Pod C B1: pump psi Hi 5500 psi	ation \Pod D\Caiculates\
Setting Input Config Calculates	Threshold Configur. Pod R Pod B Pod C B1: pump psi H 5500 psi Lo 3450 psi B2: pump flow Hi 2500 cfm	ation (Pod D)(Calculates) BD1:

bal Setting Menu

100

60 -

3000 frames

Next Can

Prev Hext Cancel

uSec/Fra

SAMPLE

Auto-Log every

instrument literally takes seconds. Simple user selections and clear, intuitive pathing make the setup process both easy to use and easy to learn. Once created, multiple test-specific setups can be stored for instant reloading.

luding

Í	armonics H	Volts2 Fund.		
ł				
ł	-			
ł				
ł				
4	-			
1		P		
Į				
1	-			
1	2.	h.		
1	1111.111	IIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIIII	IIIIIIIIIIIIIIIIIIIII	and a subscription of the
HD:	044: 62	Even: 5.8, Total:	85	
-	an Para		List	Exit